

# The choice for embedded technologies

Our microcontroller offering combines the highest performance in Flash with the lowest power consumption in the smallest packages. A comprehensive portfolio of industry-leading performers includes the latest 32-bit LPC3000, LPC2000, LH7A, LH7, and 8-bit LPC900 families. We offer an easy migration path from 8-bit to 32-bit solutions.

## LPC3000 series

The 32-bit LPC3000 series is based on the ARM926EJ core and is the only ARM9 microcontroller that provides a vector floating-point co-processor and integrated USB On-The-Go, as well as the ability to operate in ultra-low-power mode down to 0.9V. With speeds of up to 208 MHz, the NXP LPC3180 series supports Linux and WinCE and is ideal for a wide range of high-precision applications such as point-of-sale (POS) equipment, medical devices, and global positioning systems (GPS).

Type	Memory				Timers		Serial interfaces				ADC (10-bit) No. of channels	I/O pins	External bus interface	PLL	Max. freq. (MHz)	CPU voltage	I/O voltage	Temp. range options	Package	Comments / special features
	FLASH	RAM	Instruction cache	Data cache	No. of timers*	PWM channels	USB	UART	I <sup>2</sup> C	SPI										
LPC3180/01		64 K	32 K	32 K	4	2	1	7	2	2	3	55	•	•	208	1.2 V	3/1.8 V	F	LFBGA320	90-nm process, NAND Flash, SDRAM/DDR (1.8V), (1) USB 2.0 FS OTG, VFP unit, and SD card

## LH7A series

To save time-to-market for applications that use an LCD screen, these ARM922T-based microcontrollers are equipped with an LCD controller. Supported by a comprehensive set of software and hardware design tools, the LH7A series makes it easy to create everything from cost-conscious consumer systems to advanced systems with media-rich environments.

Type	Memory				Timers		Serial interfaces				ADC (10-bit) No. of channels	I/O pins	External bus interface	PLL	Max. freq. (MHz)	CPU voltage	I/O voltage	Temp. range options	Package	Comments / special features
	FLASH	RAM	Instruction cache	Data cache	No. of timers	PWM channels	USB	UART	I <sup>2</sup> C	SPI										
LH7A404		80 K Frame Buffer	8 K	8 K	5	2	1	3	0	1	10	64	•	•	266	1.8 V	3.3 V	F	LFBGA324	Integrated LCD controller. IrDA touchscreen interface. Touchscreen controller. MMU. USB 2.0 Full Speed Host/Device. 32-bit external data bus. CompactFlash. SDRAM controller. DMA controller. PCMCIA, BMI, PS/2, MMC/SD.
LH7A400		80 K Frame Buffer	8 K	8 K	5	0	1	3	0	1		60	•	•	245	1.8 V	3.3 V	F	BGA256 LFBGA256	Integrated LCD controller. IrDA. MMU. USB 2.0 Full Speed device. 32-bit external data bus. CompactFlash. SDRAM controller. MMC, PCMCIA, BMI.

## LPC2000 and LH7 series

Based on an ARM7TDMI-S core operating at up to 84 MHz, these 32-bit microcontrollers deliver high performance and low power consumption in a cost-effective package. In addition to offering integrated LCD support, they offer a wide range of peripherals, including multiple serial interfaces, Ethernet, USB Host/OTG, CAN, and external bus options and are designed for use in general-purpose and specialty embedded applications such as industrial control, automotive, medical, and connectivity.

Type	Memory		Timers		Serial interfaces								Analog		SD/MMC	I/O pins	External bus interface	PLL	Max. freq. (MHz)	CPU voltage	I/O voltage	Temp. range options	Package	Comments / special features
	FLASH	RAM	No. of timers*	PWM channels	Ethernet	USB	UART	I <sup>2</sup> C	CAN	SPI	SSP	I <sup>2</sup> S	ADC (10-bit) No. of channels	DAC (10-bit) No. of channels										
LPC2900 devices																								
LPC2919	768 K	48 K	5	24			2	2	3			16			108	•	•	80	1.8 V	3.3 V	F	LQFP144	ARM968E-S MCU with 2 LIN Master Controllers, 16 KB I-TCM, 16 KB D-TCM	
LPC2917	512 K	48 K	5	24			2	2	3			16			108	•	•	80	1.8 V	3.3 V	F	LQFP144	ARM968E-S MCU with 2 LIN Master Controllers, 16 KB I-TCM, 16 KB D-TCM	
LPC2800 devices																								
LPC2888	1M	64 K	4			1	1	1				1	5		•	•	•	60	1.8 V	3.3 V	F	TBGA180	USB V2.0 high speed; IrDA configurable; LCD interface logic; /01 version for JTAG enabled (for development), /D1 version for JTAG disabled (for production)	
LPC2880		64 K	4			1	1	1				1	5		•	•	•	60	1.8 V	3.3 V	F	TBGA180	LPC2880 is the ROMless version of the LPC2888	
LH7 devices																								
LH79525		16 K + 8 K cache	5	3	1	1	3	1		1	1	1	10			•	•	•	76	1.8 V	3.3 V	F	LQFP176	ARM720T MCU with color LCD controller. Touchscreen interface. USB 2.0 device. IrDA. SDRAM controller. MMU. DMA. NAND Flash boot. 16-bit external data bus.
LH79524		16 K + 8 K cache	5	3	1	1	3	1		1	1	1	10			•	•	•	76	1.8 V	3.3 V	F	LFPGA208	ARM720T MCU with color LCD controller. Touchscreen interface. USB 2.0 device. IrDA. SDRAM controller. MMU. DMA. NAND Flash boot. 32-bit external data bus.
LH79520		32 K + 8 K cache	6	2			3			1	1					•	•	•	77	1.8 V	3.3 V	F	LQFP176	ARM720T MCU with color LCD controller. IrDA. SDRAM controller. MMU. 32-bit external data bus.
LH75411		32 K	5	3			3			1	1		8			•	•	•	84	1.8 V	3.3 V	F	LQFP144	Color LCD controller. Touchscreen interface. DMA controller. 5-V-tolerant I/O. 16-bit external data bus.
LH75401		32 K	5	3			3		1	1	1		8			•	•	•	84	1.8 V	3.3 V	F	LQFP144	Color LCD controller. Touchscreen interface. DMA controller. 5-V-tolerant I/O. 16-bit external data bus.
LPC2400 devices																								
LPC2478	512 K	98 K	6	12	1	1	4	3	2	1	2	1	8	1	•	•	•	72		3.3 V		F	LQFP208 TFBGA208	LPC2468 with XGA LCD controller
LPC2470		98 K	6	12	1	1	4	3	2	1	2	1	8	1	•	•	•	72		3.3 V		F	LQFP208 TFBGA208	LPC2460 with XGA LCD controller
LPC2468	512 K	98 K	6	12	1	1	4	3	2	1	2	1	8	1	•	•	•	72		3.3 V		F	LQFP208 TFBGA208	On-chip 4-MHz RC-Osc, GP DMA, RTC w/ 2 K batt. RAM 2 PWM blocks; USB 2.0 FS Host/OTG/device, DMA and 4 K RAM; UART 3 w/ IrDA; 32-bit ext. bus
LPC2460		98K	6	12	1	1	4	3	2	1	2	1	8	1	•	•	•	72		3.3 V		F	LQFP208, TFBGA208	Flashless LPC2468
LPC2458	512K	98K	6	12	1	1	4	3	2	1	2	1	8	1	•	•	•	72		3.3 V		F	TFBGA180	LPC2468 with 16-bit External Memory Interface
LPC2300 devices																								
LPC2388	512K	98K	6	6	1	1	4	3	2	1	2	1	8	1	•	•	•	72		3.3 V		F	LQFP144	LPC2378 with 98 K SRAM and USB Host/OTG
LPC2387	512K	98K	6	6	1	1	4	3	2	1	2	1	6	1	•	•	•	72		3.3 V		F	LQFP100	LPC2368 with 98 K SRAM
LPC2378	512 K	58 K	6	6	1	1	4	3	2	1	2	1	8	1	•	•	•	72		3.3 V		F	LQFP144	On-chip 4MHz RC-Osc, GP DMA, RTC w/ 2 K batt. RAM USB 2.0 FS device w/ PHY, DMA and 4 K RAM; UART 3 w/ IrDA; MiniBus (8-bit)
LPC2377	512 K	58 K	6	6	1		4	3		1	2	1	8	1	•	•	•	72		3.3 V		F	LQFP144	LPC2378 without USB or CAN
LPC2368	512 K	58 K	6	6	1	1	4	3	2	1	2	1	6	1	•	•	•	72		3.3 V		F	LQFP100	100-pin version of LPC2378, no external bus
LPC2367	512 K	58 K	6	6	1		4	3		1	2	1	6	1	•	•	•	72		3.3 V		F	LQFP100	LPC2368 without USB or CAN
LPC2366	256 K	58 K	6	6	1	1	4	3	2	1	2	1	6	1	•	•	•	72		3.3 V		F	LQFP100	256 K Flash version of LPC2368, no SD/MMC

LPC2000 and LH7 series (continued)

Type	Memory		Timers		Serial interfaces							Analog		SD/MMC	I/O pins	External bus interface	PLL	Max. freq. (MHz)	CPU voltage	I/O voltage	Temp. range options	Package	Comments / special features
	FLASH	RAM	No. of timers*	PWM channels	Ethernet	USB	UART	I <sup>2</sup> C	CAN	SPI	SSP	I <sup>2</sup> S	ADC (10-bit) No. of channels										
LPC2365	256 K	58 K	6	6	1		4	3	1	2	1	6	1		70		• 72	3.3 V		F	LQFP100	LPC2366 without USB or CAN	
LPC2364	128 K	34 K	6	6	1	1	4	3	2	1	2	6	1		70		• 72	3.3 V		F	LQFP100	128 K Flash / 34 K RAM version of LPC2368, no SD/MMC	
LPC2200 devices																							
LPC2294/01	256 K	16 K	5	6			2	1	4	2		8			112	• •	60	1.8 V	3.3 V	H	LQFP144	LPC2214/01 upgrade with 4x CAN	
LPC2292/01	256 K	16 K	5	6			2	1	2	2		8			112	• •	60	1.8 V	3.3 V	F	LQFP144, TFBGA144	LPC2214/01 upgrade with 2x CAN	
LPC2290/01		64 K	5	6			2	1	2	2		8			76	• •	60	1.8 V	3.3 V	F	LQFP144	ROMless version of LPC2292/01	
LPC2220		64 K	5	6			2	1		2		8			76	• •	75	1.8 V	3.3 V	F	LQFP144, TFBGA144	64 K RAM version of LPC2210/01	
LPC2214/01	256 K	16 K	5	6			2	1		2		8			112	• •	60	1.8 V	3.3 V	F	LQFP144	External Bus, 4 Chip Selects, 10-bit SA ADC, 256 K Flash	
LPC2212/01	128 K	16 K	5	6			2	1		2		8			112	• •	60	1.8 V	3.3 V	F	LQFP144	128 K Flash version of LPC2214/01	
LPC2210/01		16 K	5	6			2	1		2		8			76	• •	60	1.8 V	3.3 V	F	LQFP144	ROMless version of LPC2214/01	
LPC2100 devices																							
LPC2194/01	256 K	16 K	5	6			2	1	4	2		4			46		• 60	1.8 V	3.3 V	H	LQFP64	LPC2124/01 upgrade with 4x CAN	
LPC2158	512 K	40 K	5	6		1	2	1		1	1	8+6	1		32		• 60	3.3 V		F	LQFP100	LPC2148 with 32 x 4 LCD driver	
LPC2157	512 K	32 K	5	6			2	1		1	1	2x8	1		32		• 60	3.3 V		F	LQFP100	LPC2138/01 with 32 x 4 LCD driver	
LPC2148	512 K	40 K	5	6		1	2	2		1	1	8+6	1		45		• 60	3.3 V		F	LQFP64	LPC2138 plus USB 2.0 full speed	
LPC2146	256 K	40 K	5	6		1	2	2		1	1	8+6	1		45		• 60	3.3 V		F	LQFP64	LPC2136 plus USB 2.0 full speed	
LPC2144	128 K	16 K	5	6		1	2	2		1	1	8+6	1		45		• 60	3.3 V		F	LQFP64	LPC2134 plus USB 2.0 full speed	
LPC2142	64 K	16 K	5	6		1	2	2		1	1	6	1		45		• 60	3.3 V		F	LQFP64	LPC2132 plus USB 2.0 full speed	
LPC2141	32 K	8 K	5	6		1	2	2		1	1	6			45		• 60	3.3 V		F	LQFP64	LPC2131 plus USB 2.0 full speed	
LPC2138/01	512 K	32 K	5	6			2	2		1	1	2x8	1		47		• 60	3.3 V		F	LQFP64, HVQFN64	Dual 8-ch. 10-bit ADC, BOD, POR, 32-kHz XTAL input, VBAT, Fast I/O	
LPC2136/01	256 K	32 K	5	6			2	2		1	1	2x8	1		47		• 60	3.3 V		F	LQFP64	256 K Flash version of LPC2138/01	
LPC2134/01	128 K	16 K	5	6			2	2		1	1	2x8	1		47		• 60	3.3 V		F	LQFP64	128 K Flash, 16 K RAM version of LPC2138/01	
LPC2132/01	64 K	16 K	5	6			2	2		1	1	8	1		47		• 60	3.3 V		F	LQFP64, HVQFN64	64 K Flash, 16 K RAM version of LPC2138/01	
LPC2131/01	32 K	8 K	5	6			2	2		1	1	8			47		• 60	3.3 V		F	LQFP64	32 K Flash, 8 K RAM version of LPC2138/01	
LPC2129/01	256 K	16 K	5	6			2	1	2	2		4			46		• 60	1.8 V	3.3 V	F	LQFP64	LPC2124/01 upgrade with 2x CAN	
LPC2119/01	128 K	16 K	5	6			2	1	2	2		4			46		• 60	1.8 V	3.3 V	F	LQFP64	LPC2114/01 upgrade with 2x CAN	
LPC2109/01	64 K	8 K	5	6			2	1	1	2		4			46		• 60	1.8 V	3.3 V	F	LQFP64	LPC2119/01 with 64 KB Flash, 8 KB RAM, and 1x CAN	
LPC2124/01	256 K	16 K	5	6			2	1		2		4			46		• 60	1.8 V	3.3 V	F	LQFP64	10-bit SA ADC, 2x SPI and 256 K Flash	
LPC2114/01	128 K	16 K	5	6			2	1		2		4			46		• 60	1.8 V	3.3 V	F	LQFP64	128 K Flash version of the LPC2124/01	
LPC2106/01	128 K	64 K	5	6			2	1		1					32		• 60	1.8 V	3.3 V	B, F	LQFP48	64 K RAM, 128 K Flash	
LPC2105/01	128 K	32 K	5	6			2	1		1					32		• 60	1.8 V	3.3 V	B	LQFP48	32 K RAM version of LPC2106/01	
LPC2104/01	128 K	16 K	5	6			2	1		1					32		• 60	1.8 V	3.3 V	B	LQFP48	16 K RAM version of LPC2106/01	
LPC2103	32 K	8 K	6	14**			2	2		1	1	8			32		• 70	1.8 V	3.3 V	F	LQFP48	Lowest cost, lowest power, ADC	
LPC2102	16 K	4 K	6	14**			2	2		1	1	8			32		• 70	1.8 V	3.3 V	F	LQFP48 HVQFN48	16 K Flash, 4 K RAM version of LPC2103	
LPC2101	8 K	2 K	6	14**			2	2		1	1	8			32		• 70	1.8 V	3.3 V	F	LQFP48	8 K Flash, 2 K RAM version of LPC2103	

Note: Reset active low. \* Includes Watchdog timer and real-time clock. \*\* Using timers 0-3.

## LPC900 series

Designed for applications that demand high integration and low cost over a wide range of performance requirements, these single-chip microcontrollers integrate a number of system-level functions.

Type	Memory			Timers			Serial interfaces			Analog			I/O pins	Frequency range (MHz) at 3 V	Temp. range options	Package	Comments / special features
	FLASH / EEPROM (program / data)	EEPROM (data)	RAM	Total no. of timers	PWM	RTC / system timer / WD	UART	I <sup>2</sup> C	SPI	ADC channels resolution	DAC channels resolution	Comparators					
<b>LPC95x devices</b>																	
P89LPC954	16 K		512 B	4	2 ch.	1	2	1	1	8/10b		2	40	0-18	F	PLCC44, LQFP44, LQFP48	LPC952 with 16 KB Flash
P89LPC952	8 K		512 B	4	2 ch.	1	2	1	1	8/10b		2	40	0-18	F	PLCC44, LQFP44	LPC900 in 44/48-pin package; 2 UARTs; 2-wire debug interface
<b>LPC940x devices</b>																	
P89LPC9408	8 K	512 B	768 B	5	CCU	1	1	1	1	8/10b		2	23	0-18	F	LQFP64	LPC938 with integrated PCF8576D universal LCD driver
P89LPC9401	8 K		256 B	4	2 ch.	1	1	1	1			2	23	0-18	F	LQFP64	LPC931 with integrated PCF8576D universal LCD driver
<b>LPC93x devices</b>																	
P89LPC938	8 K	512 B	768 B	5	CCU	1	1	1	1	8/10b		2	26	0-18	F	TSSOP28, HVQFN28, PLCC28	LPC935 with 10-bit ADC
P89LPC936	16 K	512 B	768 B	5	CCU	1	1	1	1	2x4/8b	2x8b	2	26	0-18	F	TSSOP28	LPC935 with 16K Flash
P89LPC935	8 K	512 B	768 B	5	CCU	1	1	1	1	2x4/8b	2x8b	2	26	0-18	F	TSSOP28, PLCC28, HVQFN28	LPC932A1 + two 4-ch 8-bit ADCs / two 8-bit DACs
P89LPC934	8 K		256 B	4	2 ch.	1	1	1	1	4/8b	2x8b	2	26	0-18	F	TSSOP28	LPC930/931 + 4-ch 8-bit ADC / two 8-bit DACs
P89LPC933	4 K		256 B	4	2 ch.	1	1	1	1	4/8b	2x8b	2	26	0-18	F	TSSOP28	LPC930/931 + 4-ch 8-bit ADC / two 8-bit DACs
P89LPC932A1	8 K	512 B	768 B	5	CCU	1	1	1	1			2	26	0-18	F	TSSOP28, PLCC28, HVQFN28	LPC935 without ADC and DAC
P89LPC931	8 K		256 B	4	2 ch.	1	1	1	1			2	26	0-18	F	TSSOP28	4K / 8K Flash versions of LPC932A1 w/o EEPROM, w/o CCU, w/o XRAM
P89LPC930	4 K		256 B	4	2 ch.	1	1	1	1			2	26	0-18	F	TSSOP28	4K / 8K Flash versions of LPC932A1 w/o EEPROM, w/o CCU, w/o XRAM
<b>LPC92x devices</b>																	
P89LPC925	8 K		256 B	4	2 ch.	1	1	1		4/8b	1/8b	2	18	0-18	F	TSSOP20	LPC921/922 + 4-ch 8-bit ADC / 8-bit DAC; runs up to 18 MHz
P89LPC924	4 K		256 B	4	2 ch.	1	1	1		4/8b	1/8b	2	18	0-18	F	TSSOP20	LPC921/922 + 4-ch 8-bit ADC / 8-bit DAC; runs up to 18 MHz
P89LPC9221	8 K		256 B	4	2 ch.	1	1	1				2	18	0-18	F	TSSOP20, DIP20	LPC922 with 8 high-drive pins (20 mA)
P89LPC922	8 K		256 B	4	2 ch.	1	1	1				2	18	0-18	F	TSSOP20, DIP20	20-pin versions of LPC930/931 w/o SPI; LPC76x pin-comp. upgrade
P89LPC921	4 K		256 B	4	2 ch.	1	1	1				2	18	0-18	F	TSSOP20	20-pin versions of LPC930/931 w/o SPI; LPC76x pin-comp. upgrade
P89LPC920	2 K		256 B	4	2 ch.	1	1	1				2	18	0-18	F	TSSOP20	2K Flash version of 921/922
<b>LPC91x devices</b>																	
P89LPC917	2 K		256 B	4	2 ch.	1	1	1		4/8b	1/8b	2	14	0-IRC	F	TSSOP16	4-ch 8-bit ADC / 8-bit DAC; 2 serial channels; 2-ch 8-bit PWM
P89LPC916	2 K		256 B	4	1 ch.	1	1	1	1	4/8b	1/8b	2	14	0-IRC	F	TSSOP16	4-ch 8-bit ADC / 8-bit DAC; 3 serial channels; 1-ch 8-bit PWM
P89LPC915	2 K		256 B	4	1 ch.	1	1	1		4/8b	1/8b	2	12	0-IRC	F, H	TSSOP14, DIP14	4-ch 8-bit ADC / 8-bit DAC; 2 serial channels; 1-ch 8-bit PWM
P89LPC913	1 K		128 B	4		1	1		1			2	12	0-18	F	TSSOP14	UART; SPI; 12 I/O pins; external crystal pins
P89LPC912	1 K		128 B	4	1 ch.	1			1			2	12	0-18	F	TSSOP14	1-ch 8-bit PWM; SPI; 12 I/O pins; external crystal pins
<b>LPC910x devices</b>																	
P89LPC9107	1 K		128 B	4	2 ch.	1	1			4/8b	1/8b	1	10	0-18	F	TSSOP14, DIP14	Clock doubler for internal RC OSC
P89LPC9103	1 K		128 B	4		1	1			4/8b	1/8b	1	8	0-18	F	HVSON10	Smallest available package 3 x 3 mm <sup>2</sup>
<b>LPC90x devices</b>																	
P89LPC903	1 K		128 B	4		1	1					2	6	0-IRC	F	SO8	Industry-standard pinout; 6 I/O pins; 2 analog comparators; UART
P89LPC902	1 K		128 B	4		1						2	6	0-IRC	F	SO8, DIP8	Industry-standard pinout; 6 I/O pins; 2 analog comp. 5 ext. interrupt inputs
P89LPC901	1 K		128 B	4	1 ch.	1						1	6	0-18	F	SO8, DIP8	Industry-standard pinout; 6 I/O pins; 1-ch 8-bit PWM; external crystal pins

Notes: (1) LPC900 FLASH EEPROM features: Program and data (byte) storage, block-/sector-/page-/byte-erasable, 2-ms erase, data read via MOVX instruction. (2) Auxiliary EEPROM features: Data (byte) storage, page-/byte-erasable, 2-ms erase. (3) Reset active low.

## LPC700 series

Designed for applications that demand low voltage, high integration, and low cost, the LPC700 series uses a high-performance 6-clock 80C51 that executes instructions at twice the rate of the standard 80C51. To reduce component count, board space, and system cost, the devices combine a number of system supervisory functions, serial interfaces, and analog options in low-profile SO and TSSOP packages.

Type	Memory			Timers			Serial interfaces		Analog		I/O pins	Max. frequency (MHz)	Temp. range options	Package	Comments / special features
	OTP / ROM	RAM	ICP / PP	No. of timers	PWM	WD	UART	I <sup>2</sup> C	ADC ch. / bits	Comparators					
<b>LPC76x / LPC77x devices</b>															
P87LPC779	8 K	128 B	ICP	2		•	1	1 (bit)	4/8	2	18	20	F	TSSOP20	LPC769 upgrade with 8K OTP; addtl 128 B of RAM not supported by emulators
P87LPC778	8 K	128 B	ICP	2	•	•	1	1 (bit)	4/8	2	18	20	F	TSSOP20	LPC768 upgrade with 8K OTP; addtl 128 B of RAM not supported by emulators
P87LPC769	4 K	128 B	ICP	2		•	1	1 (bit)	4/8	2	18	20	H	SO20	2 AC, BOD, POR, 8 KBIs, IRC (6 MHz ± 25%), 4ch 8-bit ADC, 2ch 8-bit DAC
P87LPC768	4 K	128 B	ICP	2	•	•	1	1 (bit)	4/8	2	18	20	B, F	DIP20, SO20	2 AC, BOD, POR, 8 KBIs, IRC (6 MHz ± 25%), 4ch 8-bit ADC, PWM
P87LPC767	4 K	128 B	ICP	2		•	1	1 (bit)	4/8	2	18	20	B, F	DIP20, SO20	2 AC, BOD, POR, 8 KBIs, IRC (6 MHz ± 25%), 4ch 8-bit ADC
P87LPC764	4 K	128 B	ICP	2		•	1	1 (bit)		2	18	20	B, F, H	TSSOP20, DIP20, SO20	2 AC, BOD, POR, 8 KBIs, IRC (6 MHz ± 10% / ± 25%)
P87LPC762	2 K	128 B	ICP	2		•	1	1 (bit)		2	18	20	B, F	TSSOP20, DIP20, SO20	2 AC, BOD, POR, 8 KBIs, IRC (6 MHz ± 10% / ± 25%)
P87LPC761	2 K	128 B	ICP	2		•	1	1 (bit)		2	14	20	B	TSSOP16, DIP16	16-pin LPC derivative; ± 2.5% internal RC Oscillator (0-50 °C)
P87LPC760	1 K	128 B	ICP	2		•	1	1 (bit)		2	12	20	B	TSSOP14, DIP14	14-pin LPC derivative; ± 2.5% internal RC Oscillator (0-50 °C)

## 80C51 family

Designed for real-time applications, these 8-bit microcontrollers are used in a wide variety of applications, from consumer products and computer peripherals to automotive systems. The NXP portfolio includes Flash, OTP (one-time programmable), ROM, and ROMless devices.

Type	Memory			Timers			Serial interfaces			I/O Pins	Max. freq. (MHz)	Temp. range options	Package	Comments / special features
	FLASH	OTP / ROM	RAM	No. of timers	PWM	WD	UART	I <sup>2</sup> C	SPI					
<b>66x devices</b>														
P89V664	64 K		2 K	4	•	•	1	2	1	36	40	F	PLCC44, LQFP44	Fast erase times and more I/O
P89V662	32 K		1 K	4	•	•	1	2	1	36	40	F	PLCC44, LQFP44	Fast erase times and more I/O
P89V660	16 K		512 B	4	•	•	1	2	1	36	40	F	PLCC44, LQFP44	Fast erase times and more I/O
<b>66xX2 devices</b>														
P87C661X2		16 K	512 B	4	•	•	1	2		32	33	B	PLCC44, LQFP44	87C660X2 with two I <sup>2</sup> C interfaces
P87C660X2		16 K	512 B	4	•	•	1	1		32	33	B, F	PLCC44, LQFP44	OTP version of 89C660; 12-clk default, 6-clk option
<b>Mx2 devices</b>														
P87C51MC2/02		96 K	3 K	4	•	•	2		1	34	24	B	PLCC44	16 MB data/code addr. range; 2 UARTs, SPI, P4 I/O
P87C51MB2/02		64 K	2 K	4	•	•	2		1	34	24	B	PLCC44	16 MB data/code addr. range; 2 UARTs, SPI, P4 I/O

Continued next page

## 80C51 family (continued)

Type	Memory			Timers			Serial interfaces			I/O Pins	Max. freq. (MHz)	Temp. range options	Package	Comments / special features
	FLASH	OTP / ROM	RAM	No. of timers	PWM	WD	UART	I <sup>2</sup> C	SPI					
<b>Rx2 devices</b>														
P89CV51RD2	64 K		1 K	4	•	•	1		1	32	33	B, F	PLCC44, TQFP44	
P89CV51RC2	32 K		1 K	4	•	•	1		1	32	33	B, F	PLCC44, TQFP44	
P89CV51RB2	16 K		1 K	4	•	•	1		1	32	33	B, F	PLCC44, TQFP44	
P89LV51RD2	64 K		1 K	4	•	•	1		1	32	33	B, F	DIP40, PLCC44, LQFP44	
P89LV51RC2	32 K		1 K	4	•	•	1		1	32	33	B, F	DIP40, PLCC44, LQFP44	
P89LV51RB2	16 K		1 K	4	•	•	1		1	32	33	B, F	PLCC44, LQFP44	
P89V51RD2	64 K		1 K	4	•	•	1		1	32	40	B, F	DIP40, PLCC44, LQFP44	
P89V51RC2	32 K		1 K	4	•	•	1		1	32	40	B, F	DIP40, PLCC44, LQFP44	
P89V51RB2	16 K		1 K	4	•	•	1		1	32	40	B, F	DIP40, PLCC44, LQFP44	
P89V52X2	8 K		256 B	4	•		1			32	33	B, F	DIP40, PLCC44, TQFP44	192B EEPROM

### Temperature Legend:

B	0 to +70 °C
F	-40 to +85 °C
H	-40 to +125 °C
J	-40 to +105 °C

### Need devices, support, and development tools?

For a list of sales offices and distributors near you, please visit [www.nxp.com/profile/sales/index.html](http://www.nxp.com/profile/sales/index.html)

For general support, please visit [www.nxp.com/microcontrollers](http://www.nxp.com/microcontrollers)

For tools, evaluation boards, and development support, please visit [www.standardics.nxp.com/support/board](http://www.standardics.nxp.com/support/board)

[www.nxp.com](http://www.nxp.com)

founded by

**PHILIPS**

© 2007 NXP B.V.

All rights reserved. Reproduction in whole or in part is prohibited without the prior written consent of the copyright owner. The information presented in this document does not form part of any quotation or contract, is believed to be accurate and reliable and may be changed without notice. No liability will be accepted by the publisher for any consequence of its use. Publication thereof does not convey nor imply any license under patent- or other industrial or intellectual property rights.

Date of release: March 2008

Document order number: 9397 750 16190

Printed in the USA